

INSTALLATION & TECHNICAL INFORMATION

PLEASE READ PRIOR TO INSTALLATION



<u>Clifford and Snell Intrinsically Safe Combination Signal</u> <u>YL50 Sounder Beacon Range</u>

VISUAL AND/OR AUDIBLE SIGNALLING DEVICES

APPROVALS AND CONFORMITIES



Website: www.moflash.com

Email: technical@moflash.co.uk

1

1.0 Introduction

The Clifford & Snell YL5IS (Yodalight) is made up of a YO5/IS/*/T* Yodalarm, certified according to BAS02ATEX1190X, and an IS signal Beacon, certified according to Baseefa05ATEX0075/2X.

Both alarm components are installed together and certified according to Baseefa08ATEX0194X. This appartus is fitted with a common Terminal Block (factory wired to the seperate PCBs) for ease of installation.

2.0 Intrinsically Safe Labelling

Each product will be given its own individual serial number, which is generated upon receipt of order. This will be printed onto the product label and attached to the side of each product. A label example is shown below:



These products have been tested by notified body Baseefa Derbyshire, and the certificates are now registered with SGS Fimko Oy (Helsinki, Finland), a notified Body for the ATEX Directive, with notified body number 0598 (as appears on the label)

The suffix X at the end of the certificate numbers indicates that there are special clauses added for safe use of these units.

3.0 Types of Approval and Standards Applied

The C&S YL5IS product has been approved to and/or conforms to the following standards: IEC 60079-0:2012 + A11:2013 IEC 60079-11:2012 EN 61241-11:2006

4.0 Zones, Groups and Temperature Classifications

The Clifford & Snell YL5IS is certified to the following:

This means that the units can be installed in locations with the following conditions when connected to an approved system:

Zones

Zone 0	Explosive gas air mixture continuously present.
Zone 1	Explosive gas air mixture likely to occur in normal operation.
Zone 2	Explosive gas air mixture not likely to occur, and if it does, it
	will only exist for a short time.
Zone 20	Explosive dust air mixture is continuously present.
Zone 21	Explosive dust air mixture likely to occur in normal operation.
Zone 22	Explosive dust air mixture not likely to occur, and if it does, it will only exist for a short time.

Gas Groupings

IIA Propane Group, IIB Ethylene Group and IIC Hydrogen and Acetylene

Dust

IIIA Fibres and Flying, IIIB Flour and Grain, IIIC Coal Dust and Metal Dust.

Ambient Conditions

Operating Temperature Range:	-25°C < Ta <40°C
Storage Temperature Range:	-40°C < Ta <70°C
Max. Relative Humidity:	95% @ 40°C

The maximum surface temperature of operating product in the unit will not exceed 190°C.

A Declaration of Conformity and the ATEX Certificates are available upon request or alternately visit <u>www.moflash.co.uk</u>.

5.0 Installation



Key Components

- 1. Lens
- 2. Beacon PCB
- 3. Back Box
- 4. Terminal Block
- 5. Sounder PCB
- 6. Sounder Front Cover
- 7. Retaining Screws
- General Requirement

The Sounder-Beacon must be installed in accordance with the latest EN60079-0 specification or equivalent IEC specification and using a suitably rated Galvanic Isolator or Zener Barrier, with consideration for any local installation requirements and should only be carried out by appropriately competent and qualified personnel.

- The location of the Sounder-Beacon should be chosen with due regard to the area over which the signalling device must be audible/ visable.
- These units are suitable for wall mounting only.
- Environmental exposure conditions during installation should be dry. Moist or wet conditions should be avoided.
- Avoid mounting the product where it may be subjected to excessive vibration.

Mounting

Devices should be mounted using the two lugs projecting from the case. The lugs are bored 8mm on 153mm centres. The minimum length of fixing screw required is 25mm. To maintain the IP rating of the enclosure, any cable entries must be fitted with a suitably rated cable gland (not included). Max cable termination 2.5mm². Dimensional drawing can be seen on page 5.

DIMENSIONAL DRAWING



6.0 Wiring

Single Stage Alarm

- · Connect the leads according to the circuit diagram
- Supply the active device with power.

The unit contains 2 printed circuit boards. The PCBs can be wired independently or can be connected together by looping in and out of the Terminal Block.

Independent wiring

A dual-channel safety barrier or double intrinsically safe connection is required.



A: +ve Beacon B: 0v Beacon C: +ve Sounder D: 0v Sounder

WARNING:

Explosion hazard due to selecting the wrong cables! Non-compliance could result in severe or fatal injuries.

If using separate safety barriers for the sounder and beacon, observe the cable specifications stated on the selected Zener barrier or the isolator certificate.

Loop in/Loop out wiring

A single-channel safety barrier or single intrinsically safe connection is required. Wires C & D are not included on delivery.



A: +ve Supply B: 0v Supply C: +ve Link Wire D: 0v Link Wire

Two Stage Alarm

The C&S YL5IS has options for first and second sounder stages.

Stage 1 tones

Selected by using the DIP switch on the Sounder PCB (Figure 8). Tone descriptions can be found in the Tone Table on Page 12.

Stage 2 tones

Each first stage tone has a pre-programmed second stage which is listed in the Tone Table. Users are able to swtich between the first and second stage tones by wiring the unit in one of 2 ways.

Second Stage Activation

3rd wire option



A dual channel barrier or double intrinsically safe connection is required.

Loop in/Loop out connection of the beacon is possible with this configuration.

2 wire option (reverse polarity)



Stage 1: A: Ov S B: +ve

Stage 1: A: Ov

B: +ve

Stage 2: A: +ve B: 0v

Stage 2: A: 0v

B: +ve C: +ve

Connect the leads according to Figure 6, Apply power as shown above for required stage.

Sounder and Beacon PCBs <u>MUST</u> be wired independently if using reverse polarity switching

Line Monitoring

If Line Monitoring is required, this can be achieved by using an end-ofline resistor. For this purpose, a wire-wound or metal film resistor with a resistance value of at least 750 Ohm and rated power of at least 2 W or a 4700 Ohm and a rated power of at least 0.4 W!

The line monitoring facility allows the integrity of the line to the sounder to be monitored through the barrier. Two sounders of the same type can be connected in parallel. The resistor can be fitted as per the diagram below (Figure 7).

Line monitoring is optional, and it is the responsibility of the system designer to decide if it is required.



Tone Selection & Volume Control

The *C&S YL5IS* unit has a total of 32 alarm tones that can be selected upon installation. This is done via the DIP switch shown below. The Tone Table is shown on page 12 of this document.



Arrange the settings of the DIP switch using a suitable tool.

- DIP switch "up" corresponds to "1"
- DIP switch "down" corresponds to "0"



Volume of the product can be reduced by adjusting the POT on the sounder PCB anticlockwise. (max reduction 15dB).

Barrier/Isolator Information

Connection into the unit must be via a suitably rated Zener Barrier or Galvanic Isolator, if these units are powered directly without a Barrier/ Isolator the PCBs will be perminantly damaged and warranty will be void

Connections for combined operation are below.

Example of single channel barrier connection



Example of dual channel barrier connection



Dual channel barriers offer the ability of more control functionality with a simple setup.

This setup would be suitable for either the independent wiring of the sounder and beacon units, or for the second stage arrangement.

Galvanic Isolators

The Glavanic Isolators have the advantage of not requiring an isolated high integrity earth to be installed, which is required for Zener Barriers. These Isolators are often more expensive per unit but may reduce installation costs as the earth is not required.



As with the Zener barriers, the Sounder and the Beacon can be triggered independently when using Galvanic Isolators, however an additional Intrinsically Safe relay is required to make the additional connection.

As with all equipment in the system, the correct ratings must be maintained to keep the integrity and safety to the correct levels. The relay can be switched to change between Sounder or Beacon or Both.

7.0 Maintenance

Little or no maintenance is required during the normal working life of the product. The C&S YL5 Intrinsically Safe enclosures are resistant to most acids, alkalis and chemicals and have been designed to withstand severe weather conditions. However it is suggested that continuous supervision and periodic inspections may be required in relation to the requirements of the installation as per IEC 60079-17.

To avoid the possibility of a potential electrostatic charge build up, it is recommended that the exterior of the product is periodically wiped down with a clean damp cloth. At this point, a visual inspection is recommended to ensure that the product is in good working order and no damage has been sustained during its normal operation.

The enclosure is non-conducting and may generate an ignition-capable level of electrostatic charge under certain extreme conditions. It is the responsibility of the user to ensure that the equipment is installed in a location where it will not be subjected to external conditions that might cause a build-up of electrostatic charge on the surface of the unit.

8.0 Conditions for Use

The C&S Intrinsically Safe Signalling Range uses an enclosure rated at IP65. To ensure that this rating is maintained once installed, a suitable cable gland must be used which matches this level of protection. The base of the unit contains one M20 appearture for cabling purposes.

Specific Conditions of Use:

- 1. Clean equipment regularly to prevent dust build-up with a damp or anti-static cloth only.
- 2. Equipment only suitable for fixed installation.
- 3. It must be ensured that the equipment is installed in accordance with IEC 60079-14 and IEC 60079-25 and that capacitance and inductance limits are not exceeded by distributed capacitance (Cc) or distributed inductance (Ic) due to cable length.

9.0 Technical Data

- Operating voltage: 16.2 26.4vDC
- Current Consumption:

Supply	Certified Barrier / Isolator Parameters	ied Barrier / Current solator Consumption rameters (Tone 1)		
24vDC	28v/300Ω	24mA	100	
18vDC	28ν/300Ω	33mA	97	

• Entity Parameters:

	Beacon	Sounder	Combined
U	30v	30v	30v
I,	200mA	133mA	133mA
P _i	0.7W	0.7W	0.7W
C _i	0	0	0
L	0	0	0

• Line Monitoring: Yes

Acoustic Data

- Volume:
- max. 105dB(A) @ 1m
- Volume Control: 15 dB(A) adjustment (T4 Models only)
- Sound Stages:
- Sound Selection: via DIP Switch

2

Luminous Characteristics

- Light Source: 8 LED Array
- Flash Rate: 60 FPM (1Hz)
- Lens Colour: Amber, Red, Green, Opal, Blue, Clear

Mechanical Data

Cable Entries: 1x M20

Material

- Enclosure: ABS UL94 5VB, FR
- Lens: Polycarbonate, UV Stable UL94 HB, FR
- Assembly Parts: Stainless Steel
- IP Rating: IP65 to IEC 60529

First Stage Tone	Tone Description	Frequency (Hz)	Repetition Rate	Second Tone Selection					on	dB(A) @	Currei Draw
				Stage	DIP Switch					1m	
				Tone	1	2	3	4	5	(±3dB)	(mA)
1	Alternating	800-1000	0.5	3	1	Ι	Ι	Ι	Ι	100	26
2	Alternating	2500-3100	0.5	4	0	Ι	Ι	Ι	1	102	34
3	Alternating (fast)	800-1000	0.25	7	1	0	Ι	Τ	Ι	100	25
4	Alternating (fast)	2500-3100	0.25	8	0	0	Ι	Τ	1	103	34
5	Alternating	440-554	0.4/0.1	14	I	Ι	0	Ι	1	98	24
6	Alternating	430-470	1.0	14	0	Ι	0	Ι	1	98	24
7	Alternating (v.fast)	800-1000	0.13	12	I	0	0	Τ	Ι	100	25
8	Alternating (v.fast)	2500-3200	0.07	13	0	0	0	Т	1	102	34
9	Alternating	440-554	2.0	10	1	Ι	Ι	0	Ι	98	24
10	Continuous Tone	700	-	1	0	Ι	Ι	0	Ι	99	25
11	Continuous Tone	1000	-	31	I	0	Ι	0	T	98	24
12	Continuous Tone	1000	-	7	0	0	Ι	0	T	101	25
13	Continuous Tone	2300	-	2	1	Ι	0	0	Ι	101	30
14	Continuous Tone	440	-	9	0	Ι	0	0	Τ	98	24
15	Interrupted Tone	1000	2.0	31	I	0	0	0	T	97	24
16	Interrupted Tone	420	1.25	30	0	0	0	0	Ι	97	24
17	Interrupted Tone	1000	0.5	1	1	Ι	Ι	Ι	0	98	24
18	Interrupted Tone	2500	0.25	4	0	Ι	Ι	Т	0	101	30
19	Interrupted Tone	2500	0.5	2	1	0	Ι	Ι	0	101	29
20	Interrupted Tone	700	6/12	10	0	0	Ι	Τ	0	100	24
21	Interrupted Tone	1000	1.0	32	1	Ι	0	Ι	0	99	24
22	Interrupted Tone	700	4.0	10	0	Ι	0	Т	0	99	24
23	Interrupted Tone	700	0.25	10	1	0	0	Ι	0	97	23
24	Interrupted Tone	720	0.7/0.3	10	0	0	0	Т	0	99	24
25	Int, fast, rising volume	1400	0.25	26	1	Ι	Ι	0	0	101	28
26	Fast siren	250-1200	0.085	11	0	Ι	Ι	0	0	99	24
27	Rising constant fall	1000	10/40/10	17	1	0	Ι	0	0	100	25
28	ISO 8201 Evacuation	800-1000	As	11	0	0	Ι	0	0	97	23
29	Fast Whoop	500-1000	0.15	32	1	Ι	0	0	0	99	25
30	Slow Whoop	500-1200	4.5	12	0	Ι	0	0	0	100	25
31	Reverse sweep	1200-500	1.0	11	1	0	0	0	0	98	24
32	Siren	500-1200	3.0	26	0	0	0	0	0	98	24

9.0 Tone Table

Moflash Signalling Limited accepts no liability for any consequences following use of this document. Any technical specifications and products referred to within this document are subject to change without notice due to continual improvement and product development policies any changes will be with consent of relavent notified body. All dB(A) figures are subject to environmental conditions. The units are sold under Moflash standard conditions of sale, available on request.

Moflash Signalling Limited, 11 Upper Conybere Street, Highgate, Birmingham, UK