B400STR Xenon Strobe Beacon



The B400 series comprises Xenon strobe beacons, permanent filament bulb or halogen beacon, blinking filament bulb or halogen beacon, rotating halogen beacon and a multi-function L.E.D. array beacon.

The surface mount base can also be supplied with a right angle bracket or with a pole mounted assembly. The B400STR Xenon beacon features an automatically synchronised flash rate of 1Hz (60 flashes per minute) as standard and also have user selectable 1.5Hz (90 flashes per minute) and double-strike flash rates.

Features

- Bayonet fixing lens.
- Anti-tamper locking screw.
- Stainless steel fixings.


Approvals

• GOST-R certificate: POCC GB.JB05.H00144.





C€ [Ĥ[LK



Specification

Light source:	Xenon Strobe	
Energy:	15 Joules (15Ws)	
Flash rate:	1Hz (60 fpm)	
	Optional 1.5Hz or double strike	
Synchronisation:	1Hz flash rate automatically synchronised	
Peak Candela:	1,500,000 cd – calculated from energy (J)	
Effective Intensity cd:	750 cd – calculated from energy (J)	
Peak Candela:	94,790 cd* - measured ref. to I.E.S.	
Effective Intensity cd:	500 cd* – measured ref. to I.E.S.	
Lens colours:	Amber, Blue, Clear, Green, Red & Yellow	
Lens type:	Prismatic (standard) or plain	
Mounting:	Surface mount (right angle or pole mount accessories available	
Entries:	1 × 5-7mm push through grommet 2 x M20 cable entry	
Dimensions:	ø140 x 220mm	
Ingress protection:	IP65	
Housing material:	ial: High impact UL94 VO (f1) PC	
Lens material:	High impact UL94 V0 (f1) PC	
Terminals:	1.5 mm² flying lead assembly	
Operating temp:	-25 to +50°C [-13° to +122°F]	
Storage temp:	-40 to +70°C [40° to +158°F]	
Relative humidity:	90% at 20°C [68°F]	
Weight:	535g/1.17lbs	
*Candala maaaaura	mante very secondation of newformance with allow loss	

*Candela measurements representative	e of	performance	with	clear	lens
at optimum voltage.					

Part Codes

Version: 24V dc/ac	Energy: 15 Joules	Part code: B400STR024B/[y]
48V dc/ac	15 Joules	B400STR048B/[y]
115V ac	15 Joules	B400STR115B/[y]
230V ac	15 Joules	B400STR230B/[y]
[y] = Lens colour:	A B C G R Y	Amber Blue Clear Green Red Yellow

Current Consumption

Current:
870mA
480mA
400mA
225mA

5 Feb 2023

E2S Warning Signals sales@e2s.com www.e2s.com

No liability is accepted for any consequence of the use of this document. The technical specification of this unit is subject to change without notice due to our policy of continual product development. All dimensions are approximate. This unit is sold subject to our standard conditions of sale, a copy of which is available on request.